

Installation Instructions





1. Position chimes in desired location, according to correct Key stage height, this may require 2 persons.

2. Mark hole locations (X4) on backboard between 1st and 2nd notes at each end, making sure instrument is level.

3. Drill hole locations (X4) according to your chosen fixings (frame fixings, wall bolts or chemical anchors) depending of the structure of the wall.

4. Fix through Backboards (X4) with suitable fixings (not supplied) in correct orientation and Key stage

5. Beaters can be fixed to Backboards or directly to wall depending on customers preference.



Wall Fixed

Rainbow Trio Chimes



Components:



Eye Straps X2



Pin Torx 25 Driver Bit X1



10x38mm Secure Screw X4

Metric Conversion:
700mm/ 28"
850mm/ 33"
1m/ 39"

Weight of heaviest part **8 kg** (chimes)



Pair Small/Large Beaters X1

Wall fixings are not supplied, installer will select suitable method of fixing.